

POWER PRODUCTS UGANDA LIMITED

PRODUCT SPECIFICATIONS



TELWIN BATTERY CHARGERS

Rubaga Kabusu

Plot 103 Rubaga Kabusu
Kampala - Masaka Road

Telephone Number(s)

+256 414 341174 | +256 392 176430
+256 758 383266 | +256 758 383340

Emails

sales@powerproductsugandaltd.com
info@powerproductsugandaltd.com

DYNAMIC 650 START

DESCRIPTION

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks.

Characteristics: Choice of normal charge, quick charge (BOOST), quick start, timer for quick charge, remote control, display of charging and starting current, protection against overloads and polarity reversal.

SPECIFICATION

| | |
|-------------------------------|-------------------------|
| Type / Category | Battery Chargers |
| Rated Charge Current | 80 A |
| Rated reference capacity | 20 / 1600 Ah |
| Charge / Start absorber Power | 2.5 / 20 Kw |
| Charge / Starter voltage | 12 / 24 V |
| Charge Current | 100 A |
| Starting Peak Current | 1000 A |
| Main Voltage | 230/400V/50/60HZ 3phase |
| Adjustment positions | 5 |
| Weight | 38 |



Rubaga Kabusu

Plot 103 Rubaga Kabusu
Kampala - Masaka Road

Telephone Number(s)

+256 414 341174 | +256 392 176430
+256 758 383266 | +256 758 383340

Emails

sales@powerproductsugandalttd.com
info@powerproductsugandalttd.com