

POWER PRODUCTS UGANDA LIMITED

PRODUCT SPECIFICATIONS



AIRMEC GENERATORS



Rubaga Kabusu

Plot 103 Rubaga Kabusu
Kampala - Masaka Road

Telephone Number(s)

+256 414 341174 | +256 392 176430
+256 758 383266 | +256 758 383340

Emails

sales@powerproductsugandaltd.com
info@powerproductsugandaltd.com

HS6500 E AVR

DESCRIPTION

- Single phase generator set with 4 stroke engine coupled on a single phase 2 pole alternator with AVR and 100% copper.
- Power 6.5kva
- Has 16A and 32A Industrial plugs
- Single phase (230v/50hz)



SPECIFICATION

Type / Category	Diesel Generator
Engine	HL 188Fv
Displacement (cc)	418
Rated Output (Kw)	6kva
Max Output (Kw)	6.5kva
Voltage (V)	230/1 Phase
Frequency (Hz)	50
Starting System	Recoil and Electric
Fuel Tank Capacity (L)	5.5
Fuel consumption at 75% load (L/Hr)	1.3
Voltage Regulation System	Automatic Voltage Regulation (AVR)
Noise level	97dB(A) @7M
Oil capacity (L)	1.1
Running Time	5 Hours
Power	9.6hp
Weight	132kg

Rubaga Kabusu

Plot 103 Rubaga Kabusu
Kampala - Masaka Road

Telephone Number(s)

+256 414 341174 | +256 392 176430
+256 758 383266 | +256 758 383340

Emails

sales@powerproductsugandalttd.com
info@powerproductsugandalttd.com