

POWER PRODUCTS UGANDA LIMITED

PRODUCT SPECIFICATIONS



LONCIN GENERATORS



Rubaga Kabusu

Plot 103 Rubaga Kabusu
Kampala - Masaka Road

Telephone Number(s)

+256 414 341174 | +256 392 176430
+256 758 383266 | +256 758 383340

Emails

sales@powerproductsugandaltd.com
info@powerproductsugandaltd.com

LC 3500DC

DESCRIPTION

Single phase generator set with 4 stroke engine coupled on a single phase 2 pole alternator 100% copper. Equipped with Voltage regulator AVR to automatically maintain a constant voltage level.



SPECIFICATION

Type / Category	Petrol Generator
Engine	G210FDA
Displacement (cc)	212
Rated Output (Kw)	2.8
Max Output (Kw)	3.1
Voltage (V)	230
Frequency (Hz)	50
Starting System	Recoil
Fuel Tank Capacity (L)	15
Voltage Regulation System	Automatic Voltage Regulation (AVR)
Noise level	72dBA@7M
Oil capacity (L)	0.6
Weight	47.5kg

Rubaga Kabusu

Plot 103 Rubaga Kabusu
Kampala - Masaka Road

Telephone Number(s)

+256 414 341174 | +256 392 176430
+256 758 383266 | +256 758 383340

Emails

sales@powerproductsugandalttd.com
info@powerproductsugandalttd.com