

POWER PRODUCTS UGANDA LIMITED

PRODUCT SPECIFICATIONS



LONCIN GENERATORS



Rubaga Kabusu

Plot 103 Rubaga Kabusu
Kampala - Masaka Road

Telephone Number(s)

+256 414 341174 | +256 392 176430
+256 758 383266 | +256 758 383340

Emails

sales@powerproductsugandaltd.com
info@powerproductsugandaltd.com

LC 6500DC

DESCRIPTION

Single phase generator set with 4 stroke engine coupled on a single phase 2 pole alternator 100% copper. Equipped with Voltage regulator AVR to automatically maintain a constant voltage level.

Rated/maximum power 5/5.5kw

Has 32A Industrial plug



SPECIFICATION

Type / Category	Petrol Generator
Engine	LC188FD
Displacement (cc)	389
Rated Output (Kw)	5
Max Output (Kw)	5.5
Voltage (V)	230
Frequency (Hz)	50
Starting System	Recoil and Electric
Fuel Tank Capacity (L)	25
Voltage Regulation System	Automatic Voltage Regulation (AVR)
Noise level	72dBA@7M
Oil capacity (L)	1.1
Weight	81kg

Rubaga Kabusu

Plot 103 Rubaga Kabusu
Kampala - Masaka Road

Telephone Number(s)

+256 414 341174 | +256 392 176430
+256 758 383266 | +256 758 383340

Emails

sales@powerproductsugandalttd.com
info@powerproductsugandalttd.com