

POWER PRODUCTS UGANDA LIMITED

PRODUCT SPECIFICATIONS



LONCIN GENERATORS

Rubaga Kabusu

Plot 103 Rubaga Kabusu
Kampala - Masaka Road

Telephone Number(s)

+256 414 341174 | +256 392 176430
+256 758 383266 | +256 758 383340

Emails

sales@powerproductsugandaltd.com
info@powerproductsugandaltd.com

LC8000DC

DESCRIPTION

Single phase generator set with 4 stroke engine coupled on a single phase 2 pole alternator 100% copper. Equipped with Voltage regulator AVR to automatically maintain a constant voltage level.



SPECIFICATION

Type / Category	Petrol Generator
Engine	LC190FD-1
Displacement (cc)	420
Rated Output (Kw)	6.0
Max Output (Kw)	6.5
Voltage (V)	220/1 Phase
Frequency (Hz)	50
Starting System	Recoil and Electric
Fuel Tank Capacity (L)	25
Voltage Regulation System	Automatic Voltage Regulation (AVR)
Noise level	77dB(A) @7M
Oil capacity (L)	1
Running Time	8 Hours
Weight	86kg

Rubaga Kabusu

Plot 103 Rubaga Kabusu
Kampala - Masaka Road

Telephone Number(s)

+256 414 341174 | +256 392 176430
+256 758 383266 | +256 758 383340

Emails

sales@powerproductsugandalttd.com
info@powerproductsugandalttd.com